

MASTERFUL ENGINEERING.

WLED
DC BATTERY BACKUP BELT DRIVE
LED WI-FI® GARAGE DOOR OPENER

MOTOR

- 12V DC
- 53 RPM
- Automatic Thermal Protection
- Permanent Lubrication

POWER

- 120V AC
- 60 Hz Voltage
- 2.7A Current Rating
- UL® Listed
- 6' Power Cord (3-Prong)

MECHANICS

- **Steel Chassis, T-Rail and Trolley**
- **Full Reinforced Belt Drive Mechanism** (63:1 Gear Reduction and Adjustable Door Arm)
- **Auto-Force** Adjustment for Changing Weather and Environmental Conditions
- **Electronic Limits** for Easy Setup
- **DC Wi-Fi Logic Board** with Built-In Surge Suppressor (for Replacement Logic Boards, Order Part 050DCTWFLK)
- **2 Lock Terminals** Allow up to 2 Locks to Be Connected (Sold Separately)

7.5"



DIMENSIONS

Rail Options	7'	8'	10'
Installed Length	125"	140"	164"
Max. Opening	7'6"	8'6"	10'6"

Headroom Clearance Required: 2"

9"

Per second for door to move upward

SPEED

6.5"

Per second for door to move downward

STANDARD SPECS.

SECURITY

SECURITY+ 2.0®

RADIO CONTROLS

Operating Range: ~200'



Operating Temperature: -40°F to 150°F

3-Button Remote Control (893MAX)

- Remote Control: 310, 315 and 390 MHz Tri-Band*
- Garage Door Opener: Frequency Agile on 310, 315 and 390 MHz
- Anti-Burglary Coding

*Tri-band on Security+ 2.0 coding only. Premium remote control is backwards compatible to all LiftMaster® openers manufactured since January 1993.

ENCRYPTED CONTROLS

Smart Control Panel® (880LMW)

- Timer-to-Close
- Program Remote Controls, Keypads and myQ Accessories
- Maintenance Alert System
- Easy Wi-Fi Setup

SMART

myQ® RADIO



- Provides 2-way communication from garage door opener and myQ Accessories.
- Enables monitoring and control of garage door openers and lighting controls via smartphone, tablet or computer.

HOMELINK® COMPATIBLE (VERSION 4.0 OR HIGHER**)

**May require an external adapter depending on the model and year of your vehicle. Visit HomeLink.com for additional information.

ELECTRICAL

LIGHTING



- 2 LED Light Panels
- 100 Points of LED Light
- 3,100 Lumens,*** 4,000 Kelvin Light Temperature
- Adjustable Time
- Disabled in Battery Backup Mode

***Verified by an independent lab.

SHIPPING.

SHIPPING WEIGHT (in lbs.)

22
HEAD

17
RAIL

3
AUTOMATIC GARAGE DOOR LOCK (OPTIONAL)

CARTONS (3)

CARTON 1: 19.81" x 11.94" x 11.19"

- Garage Door Opener Head (WLED) with Integrated Battery Backup (485LM)
- Smart Control Panel (880LMW)
- 3-Button Remote Control (893MAX)
- The Protector System® Safety Reversing Sensors

CARTON 2: 10'4" x 5" x 5" (for 7' Rail)

- Assembled Solid-Steel Belt T-Rail

CARTON 3 (OPTIONAL): 8" x 4.5" x 4"

- Automatic Garage Door Lock (841LM)

SAFETY AND SECURITY.

- Automatic Garage Door Lock Capable (2 Max.)
- Alert 2-Close/Unattended Close Operation†
- Motion Detection Feature on Control Panel
- Emergency/Quick Release
- Automatic Trolley Reconnect
- Ventilation/Pet Opening
- Down Safety Reverse
- Up Safety Stop
- Safety Beam Obstruction Turns Lights On
- Maintenance Alert System
- Garage Door Opener Capacity of up to 40 Remote Controls, 4 Wireless Keyless Entry Systems and 16 myQ Devices



6721(5,)*(5,9) 0,)/(72-133 225620

†WARNING: to reduce the risk of injury to persons— ONLY enable Timer-to-Close and myQ remote operation features when opener is installed on a sectional door.
© 2018 The Chamberlain Group, Inc. All Rights Reserved. LiftMaster, the LiftMaster logo, myQ and the myQ logo are registered trademarks of The Chamberlain Group, Inc. 300 Windsor Drive, Oak Brook, IL 60523 LiftMaster.com

ALARM.COM is a registered service mark of Alarm.com. Apple is a trademark of Apple Inc., registered in the U.S. and other countries. HomeKit is a trademark of Apple Inc. Clare Controls is a registered trademark of Clare Controls, Inc. Google, Google Home, Google Assistant and other related marks and logos are trademarks of Google Inc. Nest is a trademark of Nest Labs, Inc. XFINITY Home and the XFINITY Home design logo are trademarks or service marks of Comcast Corporation. UL® and the UL logo are trademarks of UL LLC © 2018 All Rights Reserved. Wi-Fi® is a registered trademark of Wi-Fi Alliance. HomeLink® and the HomeLink House® logo are registered trademarks of Gentex Corporation. LMGDENPGWLED 6/18

LiftMaster®